

IP BROWSER PROGRAMMABLE

QR SERIES *RESIDENTIAL AND SMALL COMMERCIAL APPLICATION*



Distinctive Ringing

Call Waiting

Do Not Disturb

Surface or Full-Flush Mount, Indoor or Outdoor

QR5IP and QR5IPFF Model

Program via any internet browser (PC, Laptop, Tablet and Smartphone)

No "Software Installation" necessary

No "Monthly Fee"

Four way to program, via LAN, WAN, Direct Connect or System's Keypad.

Selectable port, no "Dedicated Static IP" needed.

PACHCO

Since 1978

Home of Telephone Entry Access Control Systems

San Clemente, California

1-888-678-7224

www.pach-co.com

| FEATURES/MODEL | QR4 Surface | QR4FF Full Flush | QR5 Surface | QR5FF Full Flush | QR5IP Surface | QR5IPFF Full Flush |
|--|---|--|-------------------|---------------------|--|-----------------------|
| QWCM IP Browser | n/a | n/a | optional | optional | ● | ● |
| Input power 12Vac transformer supplied | 12Vac/12Vdc | 12Vac/12Vdc | 12Vac/12Vdc | 12Vac/12Vdc | 12Vac/12Vdc | 12Vac/12Vdc |
| Current consumption | 900mA | 1150mA | 1150mA | 1150mA | 1150mA | 1150mA |
| Operating temperature | 0-140 °F | 0-140 °F | 0-140 °F | 0-140 °F | 0-140 °F | 0-140 °F |
| 1x16 Backlit LCD display | n/a | n/a | ● | ● | ● | ● |
| Backlit keypad button | ● | ● | ● | ● | ● | ● |
| Tenant capacity | 1 | 1 | 10 | 10 | 10 | 10 |
| Access code capacity 4-8 digit | 50 | 50 | 100 | 100 | 100 | 100 |
| Automatic call forwarding | ● | ● | ● | ● | ● | ● |
| RemoteTouch-tone | ● | ● | ● | ● | ● | ● |
| Card/Fob capacity | n/a | n/a | 100 | 100 | 100 | 100 |
| Number of Built-inrelay form C dry contact | 2 | 2 | 2 | 2 | 2 | 2 |
| 26-Bit wiegand input | n/a | n/a | ● | ● | ● | ● |
| Built-in 26-Bit <i>proprietary</i> card reader | n/a | n/a | ● | ● | ● | ● |
| 10 - Time Zone | n/a | n/a | ● | ● | ● | ● |
| 10 - Auto unlock schedule | n/a | n/a | ● | ● | ● | ● |
| 20 - Holiday time zone | n/a | n/a | ● | ● | ● | ● |
| 10 - Unlock hold card | n/a | n/a | ● | ● | ● | ● |
| 10 - Unlock hold code 4-8 digit | n/a | n/a | ● | ● | ● | ● |
| 10 - Temporary card up to 10 times used | n/a | n/a | ● | ● | ● | ● |
| 10 - Temporary code 4-8 digit up to 10 times used | n/a | n/a | ● | ● | ● | ● |
| 2 - Auxiliary input for exit switch, postal lock | n/a | n/a | ● | ● | ● | ● |
| 2 - Door sensor | n/a | n/a | ● | ● | ● | ● |
| Unlock hold timer | n/a | n/a | ● | ● | ● | ● |
| Event recording buffer | 600 | 600 | 600 | 600 | 600 | 600 |
| Satellite Keypad, Card Reader or Combo w/ independent access | n/a | n/a | max. 8 | max. 8 | max. 8 | max. 8 |
| Mounting | INDOOR OR OUTDOOR | | | | | |
| Surface mount dimension | 6-7/16"(H) x 10-3/8"(W) x 3-1/2"(D) | | | | | |
| Full-flush mount dimension | Outside: 9-13/16"(H) x 11-13/16"(W) Inside: 7-1/2"(H) x 10-1/2"(W) x 3-5/8"(D) | | | | | |
| Warranty | 24 month | | ● <i>Included</i> | | | |
| ACCESSORIES | | | | | | |
| <u>FOR QR5, QR5FF, QR5IP, QR5IPFF</u> USCR 26-Bit Wiegand Satellite Card Reader USKP Satellite keypad QSK1000 Satellite Card Reader and Keypad UFOB Quantum Keyfob UCLAM Quantum Clam Shell Card UIISO Quantum ISO Card UCRM 26-Bit Wiegand/RS-485 controller Module UWCR 26-Bit Wiegand Reader | | <u>Pedestal Mounting Post, Adapter Plate and Mounting Ring for All QR Series</u> UPM1S Standard Single Arm (42"H, 5"x5" base) UPM4S Standard Single Arm (47"H, 5"x5" base) UPM1L Large Single Arm (47"H, 8"x8" base) UPM6L Large Single Arm (64"H, 8"x8" base) UPM8L Large Single Arm (84"H, 8"x8" base) UPM2 Double Vertical Arm (44"/84"H, 8"x8" base) UPM5 Double Horizontal Arm (47"H, 8"x8" base) UPMDB64 Single Arm Direct Buriel (64"H) UPM12E 12" Expansion Arm use for all UPM | | | <u>For All QR Series</u> QVPC Analog color camera USP1 AC and Telephone Surge Protector. USP2L Surge and Lighning Protection, <i>include Lightning on 24 months warranty</i> UBAT1 12VDC 4.5 Ahr backup battery. UXIT Multipurpose push button exit switch <i>Specifications and Warranty subject to change without prior notice</i> | |